

**MULTI COIN TIMER BOARD V5.21**

**DIP SWITCH SETTINGS**

Time for each dollar	1	2	3	4	5	6	7	8
20 sec	OFF	OFF	OFF	OFF	OFF			
40 sec	ON	OFF	OFF	OFF	OFF			
1 min	OFF	ON	OFF	OFF	OFF			
1 min 20	ON	ON	OFF	OFF	OFF			
1 min 40	OFF	OFF	ON	OFF	OFF			
2 min	ON	OFF	ON	OFF	OFF			
2 min 20	OFF	ON	ON	OFF	OFF			
2 min 40	ON	ON	ON	OFF	OFF			
3 min	OFF	OFF	OFF	ON	OFF			
3 min 20	ON	OFF	OFF	ON	OFF			
3 min 40	OFF	ON	OFF	ON	OFF			
4 min	ON	ON	OFF	ON	OFF			
4 min 20	OFF	OFF	ON	ON	OFF			
4 min 40	ON	OFF	ON	ON	OFF			
5 min	OFF	ON	ON	ON	OFF			
5 min 20	ON	ON	ON	ON	OFF			
5 min 40	OFF	OFF	OFF	OFF	ON			
6 min	ON	OFF	OFF	OFF	ON			
6 min 20	OFF	ON	OFF	OFF	ON			
6 min 40	ON	ON	OFF	OFF	ON			
7 min	OFF	OFF	ON	OFF	ON			
7 min 20	ON	OFF	ON	OFF	ON			
7 min 40	OFF	ON	ON	OFF	ON			
8 min	ON	ON	ON	OFF	ON			
8 min 20	OFF	OFF	OFF	ON	ON			
8 min 40	ON	OFF	OFF	ON	ON			
9 min	OFF	ON	OFF	ON	ON			
9 min 20	ON	ON	OFF	ON	ON			

**DESCRIPTION OF OPERATION**

Minimum price to start timer is \$1.00, made up of any combination of \$1 and \$2 coins.

The timer and relay starts 5 seconds after inserting the last coin.

Any additional coins inserted before or after the timer starts will cause a pro-rata addition to time.

A buzzer may be connected. It will pulsate for the last 20 seconds of running time.

The S5 coin mech should be set up as follows, \$1-line5, \$2-line6. Other lines not used.

*Timer Board design (C) 1995 Sunrise Microsolutions Pty Ltd, Australia. Ph (07) 5592 4076, fax (07) 5592 4078.*